



YES OPTOELECTRONICS CO.,LTD

SPECIFICATIONS

Product NO: YMS296152-0266CAAMFGN

DATE: AUG.12.2020

Prepared by	Approved by
王惠颖	牛红丽



CUSTOMER'S APPROVAL

APPROVED BY: _____ DATE: _____

YES OPTOELECTRONICS CO.,LTD

DD: No.288Yueling Road Anshan,Liaoning,CHINA

TEL: 86-412-5211859 FAX: 86-412-5211729 P.C.:114045

E-mail : yes@yes-lcd.com, yeslcd@globalsources.com

Web: <http://www.yes-lcd.com>

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 1 of 35

REVISION HISTORY

Rev	Date	Item	Page	Remark
1.0	JUN .19.2020	New Creation	ALL	
1.1	AUG.12.2020	Update Mechanical Drawing Update Interface Timing Update Command Table Update Typical Application Circuit Update Typical Operating Sequence	P5 P12 P13-24 P28 P29-30	

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 2 of 35

LIST

1. Over View-----	(4)
2. Features-----	(4)
3. Mechanical Specifications-----	(4)
4. Mechanical Drawing of EPD module-----	(5)
5. Input /Output Pin Assignment-----	(6-7)
6. Electrical Characteristics-----	(7)
6.1 Absolute Maximum Rating-----	(7)
6.2 Panel DC Characteristics-----	(8)
6.3 Panel DC Characteristics(Driver IC Internal Regulators)-----	(9)
6.4 Panel AC Characteristics-----	(9)
6.4.1 MCU Interface Selection -----	(9)
6.4.2 MCU Serial Interface(4-wire SPI) -----	(9-10)
6.4.3 MCU Serial Interface(3-wire SPI) -----	(11)
6.4.4 Interface Timing-----	(12)
7. Command Table -----	(13-24)
8. Optical Specifications -----	(25)
9. Handling, Safety and Environment Requirements -----	(25)
10. Reliability test-----	(26)
11. Block Diagram-----	(27)
12. Typical Application Circuit-----	(28)
13. Typical Operating Sequence -----	(29)
13.1 Normal Operation Flow-----	(29)
13.2 OTP Operation Flow-----	(30)
13.3 OTP Operation Reference Program Code-----	(30)
14 Part Number Definition-----	(31)
15 Inspection condition-----	(31)
15.1 Environment-----	(31)
15.2 Illuminance-----	(31)
15.3 Inspect method-----	(31)
15.4 Display area-----	(31)
15.5 Inspection standard-----	(32)
15.5.1 Electric inspection standard-----	(32)
15.5.2 Appearance inspection standard-----	(33-34)
16 Packaging-----	(35)

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 3 of 35

1. Over View

YMS296152-0266CAAMFGN is an Active Matrix Electrophoretic Display (AM EPD), with interface and a reference system design. The display is capable to display images at 1-bit white, black full display capabilities. The 2.66 inch active area contains 296×152 pixels. The module is a TFT-array driving electrophoresis display, with integrated circuits including gate driver, source driver, MCU interface, timing controller, oscillator, DC-DC, SRAM, LUT, VCOM. Module can be used in portable electronic devices, such as Electronic Shelf Label (ESL) System.

2. Features


- 296×152 pixels display
- High contrast High reflectance
- Ultra wide viewing angle Ultra low power consumption
- Pure reflective mode
- Bi-stable display
- Commercial temperature range
- Landscape portrait modes
- Hard-coat antiglare display surface
- Ultra Low current deep sleep mode
- On chip display RAM
- Waveform can stored in On-chip OTP or written by MCU
- Serial peripheral interface available
- On-chip oscillator
- On-chip booster and regulator control for generating VCOM, Gate and Source driving voltage
- I²C signal master interface to read external temperature sensor
- Built-in temperature sensor

3. Mechanical Specifications

Parameter	Specifications	Unit	Remark
Screen Size	2.66	Inch	
Display Resolution	152(H)×296(V)	Pixel	Dpi:125
Active Area	30.704×60.088	mm	
Pixel Pitch	0.202×0.203	mm	
Pixel Configuration	Rectangle		
Outline Dimension	36.30(H)×71.82(V) ×1.0(D)	mm	
Weight	4.7±0.5	g	

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 4 of 35

4. Mechanical Drawing of EPD module



DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 5 of 35

5. Input /Output Pin Assignment

No.	Name	I/O	Description	Remark
1	NC		Do not connect with other NC pins	Keep Open
2	GDR	O	N-Channel MOSFET Gate Drive Control	
3	RESE	I	Current Sense Input for the Control Loop	
4	NC	NC	Do not connect with other NC pins	Keep Open
5	VSH2	C	Positive Source driving voltage(Red)	
6	TSCL	O	I ² C Interface to digital temperature sensor Clock pin	
7	TSDA	I/O	I ² C Interface to digital temperature sensor Data pin	
8	BS1	I	Bus Interface selection pin	Note 5-5
9	BUSY	O	Busy state output pin	Note 5-4
10	RES#	I	Reset signal input. Active Low.	Note 5-3
11	D/C#	I	Data /Command control pin	Note 5-2
12	CS#	I	Chip select input pin	Note 5-1
13	SCL	I	Serial Clock pin (SPI)	
14	SDA	I	Serial Data pin (SPI)	
15	VDDIO	P	Power Supply for interface logic pins It should be connected with VCI	
16	VCI	P	Power Supply for the chip	
17	VSS	P	Ground	
18	VDD	C	Core logic power pin VDD can be regulated internally from VCI. A capacitor should be connected between VDD and VSS	
19	VPP	P	FOR TEST	
20	VSH1	C	Positive Source driving voltage	
21	VGH	C	Power Supply pin for Positive Gate driving voltage and VSH1	
22	VSL	C	Negative Source driving voltage	
23	VGL	C	Power Supply pin for Negative Gate driving voltage VCOM and VSL	
24	VCOM	C	VCOM driving voltage	

DATE AUG.12.2020

Version

1.1

TECHNICAL SPECIFICATION

LCM

YES

YMS296152-0266CAAMFGN

Page 6 of 35

I = Input Pin, O =Output Pin, /O = Bi-directional Pin (Input/output), P = Power Pin, C = Capacitor Pin

Note 5-1: This pin (CS#) is the chip select input connecting to the MCU. The chip is enabled for MCU communication only when CS# is pulled LOW.

Note 5-2: This pin is (D/C#) Data/Command control pin connecting to the MCU in 4-wire SPI mode. When the pin is pulled HIGH, the data at SDA will be interpreted as data. When the pin is pulled LOW, the data at SDA will be interpreted as command.

Note 5-3: This pin (RES#) is reset signal input. The Reset is active low.

Note 5-4: This pin is Busy state output pin. When Busy is High, the operation of chip should not be interrupted, command should not be sent. The chip would put Busy pin High when -Outputting display waveform -Communicating with digital temperature sensor

Note 5-5: Bus interface selection pin

BS1 State	MCU Interface
L	4-lines serial peripheral interface(SPI) - 8 bits SPI
H	3- lines serial peripheral interface(SPI) - 9 bits SPI

6. Electrical Characteristics

6.1 Absolute Maximum Rating

Parameter	Symbol	Rating	Unit
Logic supply voltage	VCI	-0.5 to +4.0	V
Logic Input voltage	VIN	-0.5 to VCI +0.5	V
Logic Output voltage	VOUT	-0.5 to VCI +0.5	V
Operating Temp range	TOPR	0 to +50	°C
Storage Temp range	TSTG	-25 to+70	°C
Optimal Storage Temp	TSTGo	23±2	°C
Optimal Storage Humidity	HSTGo	55±10	%RH

Note: Maximum ratings are those values beyond which damages to the device may occur. Functional operation should be restricted to the limits in the Panel DC Characteristics tables.


DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 7 of 35

6.2 Panel DC Characteristics

The following specifications apply for: VSS=0V, VCI=3.0V, TOPR =25°C.

Parameter	Symbol	Conditions	Applicable pin	Min.	Typ.	Max	Units
Single ground	V _{SS}	-		-	0	-	V
Logic supply voltage	V _{CI}	-	VCI	2.2	3.0	3.7	V
Core logic voltage	V _{DD}		VDD	1.7	1.8	1.9	V
High level input voltage	V _{IH}	-	-	0.8 V _{CI}	-	-	V
Low level input voltage	V _{IL}	-	-	-	-	0.2 V _{CI}	V
High level output voltage	V _{OH}	IOH = -100uA	-	0.9 V _{CI}	-	-	V
Low level output voltage	V _{OL}	IOL = 100uA	-	-	-	0.1 V _{CI}	V
Typical power	P _{TYP}	V _{CI} =3.0V	-	-	9.0	-	mW
Deep sleep mode	P _{STPY}	V _{CI} =3.0V	-	-	0.003	-	mW
Typical operating current	Iopr_V _{CI}	V _{CI} =3.0V	-	-	3.0	-	mA
Image update time	-	25 °C	-	-	3	-	sec
Sleep mode current	Islp_V _{CI}	DC/DC off No clock No input load Ram data retain	-	-	20		uA
Deep sleep mode current	Idslp_V _{CI}	DC/DC off No clock No input load Ram data not retain	-	-	2	6	uA

Notes: 1. The typical power is measured with following transition from horizontal 2 scale pattern to vertical 2 scale pattern.



2. The deep sleep power is the consumed power when the panel controller is in deep sleep mode.
3. The listed electrical/optical characteristics are only guaranteed under the controller & waveform provided by YES.

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 8 of 35

6.3 Panel DC Characteristics(Driver IC Internal Regulators)

The following specifications apply for: VSS=0V, VCI=3.0V, TOPR =25°C.

Parameter	Symbol	Condition	Applicable pin	Min.	Typ.	Max.	Unit
VCOM output voltage	VCOM	-	VCOM	-	TBD	-	V
Positive Source output voltage	V _{SH}	-	S ₀ ~S ₁₅₁	+14.5	+15	+15.5	V
Negative Source output voltage	V _{SL}	-	S ₀ ~S ₁₅₁	-15.5	-15	-14.5	V
Positive gate output voltage	V _{gh}	-	G ₀ ~G ₂₉₅	+21	+22	+23	V
Negative gate output voltage	V _{gl}	-	G ₀ ~G ₂₉₅	-21	-20	-19	V

6.4 Panel AC Characteristics

The pin assignment at different interface mode is summarized in Table 6-4-1. Different MCU mode can be set by hardware selection on BS1 pins. The display panel only supports 4-wire SPI or 3-wire SPI interface mode.

Pin Name	Data/Command Interface		Control Signal		
	Bus interface	SDA	SCL	CS#	D/C#
BS1=L 4-wire SPI	SDA	SCL	CS#	D/C#	RES#
BS1=H 3-wire SPI	SDA	SCL	CS#	L	RES#

6.4.2 MCU Serial Interface (4-wire SPI)

The serial interface consists of serial clock SCL, serial data SDA, D/C#, CS#. This interface supports Write mode and Read mode.


Function	CS#	D/C#	SCL
Write command	L	L	↑
Write data	L	H	↑

Note: ↑ stands for rising edge of signal

In the write mode SDA is shifted into an 8-bit shift register on every rising edge of SCL in the order of D7, D6, ... D0. The level of D/C# should be kept over the whole byte. The data byte in the shift register is written to the Graphic Display Data RAM /Data Byte register or command Byte register according to D/C# pin.

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 9 of 35


Figure 6-1: Write procedure in 4-wire SPI mode



In the Read mode:

1. After driving CS# to low, MCU need to define the register to be read.
2. SDA is shifted into an 8-bit shift register on every rising edge of SCL in the order of D7, D6, ... D0 with D/C# keep low.
3. After SCL change to low for the last bit of register, D/C# need to drive to high.
4. SDA is shifted out an 8-bit data on every falling edge of SCL in the order of D7, D6, ... D0.
5. Depending on register type, more than 1 byte can be read out. After all byte are read, CS# need to drive to high to stop the read operation.

Figure 6-2: Read procedure in 4-wire SPI mode



DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 10 of 35

6.4.3 MCU Serial Interface (3-wire SPI)


The 3-wire serial interface consists of serial clock SCL, serial data SDA and CS#. This interface also supports Write mode and Read mode.

The operation is similar to 4-wire serial interface while D/C# pin is not used. There are altogether 9-bits will be shifted into the shift register on every ninth clock in sequence: D/C# bit, D7 to D0 bit. The D/C# bit (first bit of the sequential data) will determine the following data byte in the shift register is written to the Display Data RAM (D/C# bit = 1) or the command register (D/C# bit = 0).

Function	CS#	D/C#	SCL
Write command	L	Tie	↑
Write data	L	Tie	↑

Note: ↑ stands for rising edge of signal

Figure 6-3: Write procedure in 3-wire SPI mode




In the Read mode:

1. After driving CS# to low, MCU need to define the register to be read.
2. D/C=0 is shifted thru SDA with one rising edge of SCL
3. SDA is shifted into an 8-bit shift register on every rising edge of SCL in the order of D7, D6, ... D0.
4. D/C=1 is shifted thru SDA with one rising edge of SCL
5. SDA is shifted out an 8-bit data on every falling edge of SCL in the order of D7, D6, ... D0.
6. Depending on register type, more than 1 byte can be read out. After all byte are read, CS# need to drive to high to stop the read operation.


DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 11 of 35

Figure 6-4: Read procedure in 3-wire SPI mode



6.4.4 Interface Timing

The following specifications apply for: VSS=0V, VCI=3.0V, TOPR =25°C.



Changed Diagram

Serial Interface Timing Characteristics

(VCI - VSS = 2.2V to 3.7V, TOPR = 25°C, CL=20pF)

Write mode

Symbol	Parameter	Min	Typ	Max	Unit
f _{SCL}	SCL frequency (Write Mode)	-	-	20	MHz
t _{CSSU}	Time CS# has to be low before the first rising edge of SCLK	60	-	-	ns
t _{CSSHD}	Time CS# has to remain low after the last falling edge of SCLK	65	-	-	ns
t _{CSHIGH}	Time CS# has to remain high between two transfers	100	-	-	ns
t _{SCLHIGH}	Part of the clock period where SCL has to remain high	25	-	-	ns
t _{SCLLOW}	Part of the clock period where SCL has to remain low	25	-	-	ns
t _{SISU}	Time SI (SDA Write Mode) has to be stable before the next rising edge of SCL	10	-	-	ns
t _{SIHLD}	Time SI (SDA Write Mode) has to remain stable after the rising edge of SCL	40	-	-	ns

Read mode

Symbol	Parameter	Min	Typ	Max	Unit
f _{SCL}	SCL frequency (Read Mode)	-	-	2.5	MHz
t _{CSSU}	Time CS# has to be low before the first rising edge of SCLK	100	-	-	ns
t _{CSSHD}	Time CS# has to remain low after the last falling edge of SCLK	50	-	-	ns
t _{CSHIGH}	Time CS# has to remain high between two transfers	250	-	-	ns
t _{SCLHIGH}	Part of the clock period where SCL has to remain high	180	-	-	ns
t _{SCLLOW}	Part of the clock period where SCL has to remain low	180	-	-	ns
t _{SOSU}	Time SO (SDA Read Mode) will be stable before the next rising edge of SCL	-	50	-	ns
t _{SOHLD}	Time SO (SDA Read Mode) will remain stable after the falling edge of SCL	-	0	-	ns

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 12 of 35

7. Command Table

Command Table											Command	Description																																																							
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0																																																									
0	0	01	0	0	0	0	0	0	0	1	Driver Output control	Gate setting A[8:0]= 127h [POR], 296 MUX MUX Gate lines setting as (A[8:0] + 1). B [2:0] = 000 [POR]. Gate scanning sequence and direction B[2]: GD Selects the 1st output Gate GD=0 [POR], G0 is the 1st gate output channel, gate output sequence is G0,G1, G2, G3, ... GD=1, G1 is the 1st gate output channel, gate output sequence is G1, G0, G3, G2, ... B[1]: SM Change scanning order of gate driver. SM=0 [POR], G0, G1, G2, G3...295 (left and right gate interlaced) SM=1, G0, G2, G4 ...G294, G1, G3, ...G295 B[0]: TB TB = 0 [POR], scan from G0 to G295 TB = 1, scan from G295 to G0.																																																							
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																																																									
0	1		0	0	0	0	0	0	0	A ₈																																																									
0	1		0	0	0	0	0	B ₂	B ₁	B ₀																																																									
0	0	03	0	0	0	0	0	0	1	1	Gate Driving voltage Control	Set Gate driving voltage A[4:0] = 00h [POR] VGH setting from 10V to 20V																																																							
0	1		0	0	0	A ₄	A ₃	A ₂	A ₁	A ₀																																																									
											<table border="1"> <thead> <tr> <th>A[4:0]</th> <th>VGH</th> <th>A[4:0]</th> <th>VGH</th> </tr> </thead> <tbody> <tr> <td>00h</td> <td>20</td> <td>0Dh</td> <td>15</td> </tr> <tr> <td>03h</td> <td>10</td> <td>0Eh</td> <td>15.5</td> </tr> <tr> <td>04h</td> <td>10.5</td> <td>0Fh</td> <td>16</td> </tr> <tr> <td>05h</td> <td>11</td> <td>10h</td> <td>16.5</td> </tr> <tr> <td>06h</td> <td>11.5</td> <td>11h</td> <td>17</td> </tr> <tr> <td>07h</td> <td>12</td> <td>12h</td> <td>17.5</td> </tr> <tr> <td>08h</td> <td>12.5</td> <td>13h</td> <td>18</td> </tr> <tr> <td>07h</td> <td>12</td> <td>14h</td> <td>18.5</td> </tr> <tr> <td>08h</td> <td>12.5</td> <td>15h</td> <td>19</td> </tr> <tr> <td>09h</td> <td>13</td> <td>16h</td> <td>19.5</td> </tr> <tr> <td>0Ah</td> <td>13.5</td> <td>17h</td> <td>20</td> </tr> <tr> <td>0Bh</td> <td>14</td> <td>Other</td> <td>NA</td> </tr> <tr> <td>0Ch</td> <td>14.5</td> <td></td> <td></td> </tr> </tbody> </table>	A[4:0]	VGH	A[4:0]	VGH	00h	20	0Dh	15	03h	10	0Eh	15.5	04h	10.5	0Fh	16	05h	11	10h	16.5	06h	11.5	11h	17	07h	12	12h	17.5	08h	12.5	13h	18	07h	12	14h	18.5	08h	12.5	15h	19	09h	13	16h	19.5	0Ah	13.5	17h	20	0Bh	14	Other	NA	0Ch	14.5		
A[4:0]	VGH	A[4:0]	VGH																																																																
00h	20	0Dh	15																																																																
03h	10	0Eh	15.5																																																																
04h	10.5	0Fh	16																																																																
05h	11	10h	16.5																																																																
06h	11.5	11h	17																																																																
07h	12	12h	17.5																																																																
08h	12.5	13h	18																																																																
07h	12	14h	18.5																																																																
08h	12.5	15h	19																																																																
09h	13	16h	19.5																																																																
0Ah	13.5	17h	20																																																																
0Bh	14	Other	NA																																																																
0Ch	14.5																																																																		

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 13 of 35

Command Table												Command	Description	
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0				
0	0	04	0	0	0	0	0	1	0	0	Source Driving voltage Control		Set Source driving voltage A[7:0] = 41h [POR], VSH1 at 15V B [7:0] = A8h [POR], VSH2 at 5V. C[7:0] = 32h [POR], VSL at -15V Remark: VSH1>=VSH2	
0	1		A7	A6	A5	A4	A3	A2	A1	A0				
0	1		B7	B6	B5	B4	B3	B2	B1	B0				
0	1		C7	C6	C5	C4	C3	C2	C1	C0				
A[7]/B[7] = 1, VSH1/VSH2 voltage setting from 2.4V to 8.8V				A[7]/B[7] = 0, VSH1/VSH2 voltage setting from 9V to 17V				C[7] = 0, VSL setting from -5V to -17V						
A/B[7:0]	VSH1/VSH2	A/B[7:0]	VSH1/VSH2	A/B[7:0]	VSH1/VSH2	A/B[7:0]	VSH1/VSH2	C[7:0]	VSL					
8Eh	2.4	AFh	5.7	23h	9	3Ch	14	0Ah	-5					
8Fh	2.5	B0h	5.8	24h	9.2	3Dh	14.2	0Ch	-5.5					
90h	2.6	B1h	5.9	25h	9.4	3Eh	14.4	0Eh	-6					
91h	2.7	B2h	6	26h	9.6	3Fh	14.6	10h	-6.5					
92h	2.8	B3h	6.1	27h	9.8	40h	14.8	12h	-7					
93h	2.9	B4h	6.2	28h	10	41h	15	14h	-7.5					
94h	3	B5h	6.3	29h	10.2	42h	15.2	16h	-8					
95h	3.1	B6h	6.4	2Ah	10.4	43h	15.4	18h	-8.5					
96h	3.2	B7h	6.5	2Bh	10.6	44h	15.6	1Ah	-9					
97h	3.3	B8h	6.6	2Ch	10.8	45h	15.8	1Ch	-9.5					
98h	3.4	B9h	6.7	2Dh	11	46h	16	1Eh	-10					
99h	3.5	BAh	6.8	2Eh	11.2	47h	16.2	1Ah	-10.5					
9Ah	3.6	BBh	6.9	2Fh	11.4	48h	16.4	20h	-11					
9Bh	3.7	BCh	7	30h	11.6	49h	16.6	22h	-11.5					
9Ch	3.8	BDh	7.1	31h	11.8	4Ah	16.8	24h	-11.5					
9Dh	3.9	BEh	7.2	32h	12	4Bh	17	26h	-12					
9Eh	4	BFh	7.3	33h	12.2	Other	NA	28h	-12.5					
9Fh	4.1	C0h	7.4	34h	12.4			2Ah	-13					
A0h	4.2	C1h	7.5	35h	12.6			2Ch	-13.5					
A1h	4.3	C2h	7.6	36h	12.8			2Eh	-14					
A2h	4.4	C3h	7.7	37h	13			30h	-14.5					
A3h	4.5	C4h	7.8	38h	13.2			32h	-15					
A4h	4.6	C5h	7.9	39h	13.4			34h	-15.5					
A5h	4.7	C6h	8	3Ah	13.6			36h	-16					
A6h	4.8	C7h	8.1	3Bh	13.8			38h	-16.5					
A7h	4.9	C8h	8.2					3Ah	-17					
A8h	5	C9h	8.3					Other	NA					
A9h	5.1	CAh	8.4											
AAh	5.2	CBh	8.5											
ABh	5.3	CCh	8.6											
ACh	5.4	CDh	8.7											
ADh	5.5	CEh	8.8											
A Eh	5.6	Other	NA											
0	0	08	0	0	0	0	1	0	0	0	Initial Code Setting OTP Program		Program Initial Code Setting The command required CLKEN=1. Refer to Register 0x22 for detail. BUSY pad will output high during operation.	
0	0	09	0	0	0	0	1	0	0	1	Write Register for Initial Code Setting		Write Register for Initial Code Setting Selection A[7:0] ~ D[7:0]: Reserved Details refer to Application Notes of Initial Code Setting	
0	1		A7	A6	A5	A4	A3	A2	A1	A0				
0	1		B7	B6	B5	B4	B3	B2	B1	B0				
0	1		C7	C6	C5	C4	C3	C2	C1	C0				
0	1		D7	D6	D5	D4	D3	D2	D1	D0				
0	0	0A	0	0	0	0	1	0	1	0	Read Register for Initial Code Setting		Read Register for Initial Code Setting	

DATE	AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM		YES	YMS296152-0266CAAMFGN	Page 14 of 35

Command Table											Command	Description																																															
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0																																																	
0	0	0C	0	0	0	0	1	1	0	0	Booster Soft start Control	Booster Enable with Phase 1, Phase 2 and Phase 3 for soft start current and duration setting. A[7:0] -> Soft start setting for Phase1 = 8Bh [POR] B[7:0] -> Soft start setting for Phase2 = 9Ch [POR] C[7:0] -> Soft start setting for Phase3 = 96h [POR] D[7:0] -> Duration setting = 0Fh [POR] Bit Description of each byte: A[6:0] / B[6:0] / C[6:0]:																																															
0	1		1	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																																																	
0	1		1	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀																																																	
0	1		1	C ₆	C ₅	C ₄	C ₃	C ₂	C ₁	C ₀																																																	
0	1		0	0	D ₅	D ₄	D ₃	D ₂	D ₁	D ₀																																																	
												<table border="1"> <thead> <tr> <th>Bit[6:4]</th> <th>Driving Strength Selection</th> </tr> </thead> <tbody> <tr><td>000</td><td>1(Weakest)</td></tr> <tr><td>001</td><td>2</td></tr> <tr><td>010</td><td>3</td></tr> <tr><td>011</td><td>4</td></tr> <tr><td>100</td><td>5</td></tr> <tr><td>101</td><td>6</td></tr> <tr><td>110</td><td>7</td></tr> <tr><td>111</td><td>8(Strongest)</td></tr> </tbody> </table> <table border="1"> <thead> <tr> <th>Bit[3:0]</th> <th>Min Off Time Setting of GDR [Time unit]</th> </tr> </thead> <tbody> <tr><td>0000</td><td rowspan="2">NA</td></tr> <tr><td>0011</td></tr> <tr><td>0100</td><td>2.6</td></tr> <tr><td>0101</td><td>3.2</td></tr> <tr><td>0110</td><td>3.9</td></tr> <tr><td>0111</td><td>4.6</td></tr> <tr><td>1000</td><td>5.4</td></tr> <tr><td>1001</td><td>6.3</td></tr> <tr><td>1010</td><td>7.3</td></tr> <tr><td>1011</td><td>8.4</td></tr> <tr><td>1100</td><td>9.8</td></tr> <tr><td>1101</td><td>11.5</td></tr> <tr><td>1110</td><td>13.8</td></tr> <tr><td>1111</td><td>16.5</td></tr> </tbody> </table> D[5:0]: duration setting of phase D[5:4]: duration setting of phase 3 D[3:2]: duration setting of phase 2 D[1:0]: duration setting of phase 1	Bit[6:4]	Driving Strength Selection	000	1(Weakest)	001	2	010	3	011	4	100	5	101	6	110	7	111	8(Strongest)	Bit[3:0]	Min Off Time Setting of GDR [Time unit]	0000	NA	0011	0100	2.6	0101	3.2	0110	3.9	0111	4.6	1000	5.4	1001	6.3	1010	7.3	1011	8.4	1100	9.8	1101	11.5	1110	13.8	1111	16.5
Bit[6:4]	Driving Strength Selection																																																										
000	1(Weakest)																																																										
001	2																																																										
010	3																																																										
011	4																																																										
100	5																																																										
101	6																																																										
110	7																																																										
111	8(Strongest)																																																										
Bit[3:0]	Min Off Time Setting of GDR [Time unit]																																																										
0000	NA																																																										
0011																																																											
0100	2.6																																																										
0101	3.2																																																										
0110	3.9																																																										
0111	4.6																																																										
1000	5.4																																																										
1001	6.3																																																										
1010	7.3																																																										
1011	8.4																																																										
1100	9.8																																																										
1101	11.5																																																										
1110	13.8																																																										
1111	16.5																																																										
												<table border="1"> <thead> <tr> <th>Bit[1:0]</th> <th>Duration of Phase [Approximation]</th> </tr> </thead> <tbody> <tr><td>00</td><td>10ms</td></tr> <tr><td>01</td><td>20ms</td></tr> <tr><td>10</td><td>30ms</td></tr> <tr><td>11</td><td>40ms</td></tr> </tbody> </table>	Bit[1:0]	Duration of Phase [Approximation]	00	10ms	01	20ms	10	30ms	11	40ms																																					
Bit[1:0]	Duration of Phase [Approximation]																																																										
00	10ms																																																										
01	20ms																																																										
10	30ms																																																										
11	40ms																																																										

0	0	10	0	0	0	1	0	0	0	0	Deep Sleep mode	Deep Sleep mode Control: A[1:0] : Description <table border="1"> <tbody> <tr><td>00</td><td>Normal Mode [POR]</td></tr> <tr><td>01</td><td>Enter Deep Sleep Mode 1</td></tr> <tr><td>11</td><td>Enter Deep Sleep Mode 2</td></tr> </tbody> </table> After this command initiated, the chip will enter Deep Sleep Mode, BUSY pad will keep output high. Remark: To Exit Deep Sleep mode, User required to send HWRESET to the driver	00	Normal Mode [POR]	01	Enter Deep Sleep Mode 1	11	Enter Deep Sleep Mode 2
00	Normal Mode [POR]																	
01	Enter Deep Sleep Mode 1																	
11	Enter Deep Sleep Mode 2																	
0	1		0	0	0	0	0	0	A ₁	A ₀								

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 15 of 35

Command Table

R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description
0	0	11	0	0	0	1	0	0	0	1	Data Entry mode setting	Define data entry sequence A[2:0] = 011 [POR] A [1:0] = ID[1:0] Address automatic increment / decrement setting The setting of incrementing or decrementing of the address counter can be made independently in each upper and lower bit of the address. 00 –Y decrement, X decrement, 01 –Y decrement, X increment, 10 –Y increment, X decrement, 11 –Y increment, X increment [POR] A[2] = AM Set the direction in which the address counter is updated automatically after data are written to the RAM. AM= 0, the address counter is updated in the X direction. [POR] AM = 1, the address counter is updated in the Y direction.
0	1		0	0	0	0	0	A ₂	A ₁	A ₀		
0	0	12	0	0	0	1	0	0	1	0	SW RESET	It resets the commands and parameters to their S/W Reset default values except R10h-Deep Sleep Mode During operation, BUSY pad will output high. Note: RAM are unaffected by this command.
0	0	14	0	0	0	1	0	1	0	0	HV Ready Detection	HV ready detection A[7:0] = 00h [POR] The command required CLKEN=1 and ANALOGEN=1. Refer to Register 0x22 for detail. After this command initiated, HV Ready detection starts. BUSY pad will output high during detection. The detection result can be read from the Status Bit Read (Command 0x2F). A[6:4]=n for cool down duration: 10ms x (n+1) A[2:0]=m for number of Cool Down Loop to detect. The max HV ready duration is 10ms x (n+1) x (m) HV ready detection will be trigger after each cool down time. The detection will be completed when HV is ready. For 1 shot HV ready detection, A[7:0] can be set as 00h.
0	1		0	A ₆	A ₅	A ₄	0	A ₂	A ₁	A ₀		

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 16 of 35

Command Table												Command	Description														
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0																	
0	0	15	0	0	0	1	0	1	0	1		VCI Detection	VCI Detection A[2:0] = 100 [POR] , Detect level at 2.3V A[2:0] : VCI level Detect														
0	1		0	0	0	0	0	A ₂	A ₁	A ₀			<table border="1"> <tr> <th>A[2:0]</th> <th>VCI level</th> </tr> <tr> <td>011</td> <td>2.2V</td> </tr> <tr> <td>100</td> <td>2.3V</td> </tr> <tr> <td>101</td> <td>2.4V</td> </tr> <tr> <td>110</td> <td>2.5V</td> </tr> <tr> <td>111</td> <td>2.6V</td> </tr> <tr> <td>Other</td> <td>NA</td> </tr> </table> <p>The command required CLKEN=1 and ANALOGEN=1 Refer to Register 0x22 for detail.</p> <p>After this command initiated, VCI detection starts. BUSY pad will output high during detection. The detection result can be read from the Status Bit Read (Command 0x2F).</p>	A[2:0]	VCI level	011	2.2V	100	2.3V	101	2.4V	110	2.5V	111	2.6V	Other	NA
A[2:0]	VCI level																										
011	2.2V																										
100	2.3V																										
101	2.4V																										
110	2.5V																										
111	2.6V																										
Other	NA																										
0	0	18	0	0	0	1	1	0	0	0		Temperature Sensor Control	Temperature Sensor Selection A[7:0] = 48h [POR], external temperature sensor A[7:0] = 80h Internal temperature sensor														
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																	
0	0	1A	0	0	0	1	1	0	1	0		Temperature Sensor Control (Write to temperature register)	Write to temperature register. A[7:0] = 7Fh [POR]														
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																	
0	0	1B	0	0	0	1	1	0	1	1		Temperature Sensor Control (Read from temperature register)	Read from temperature register.														
1	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																	
0	0	1C	0	0	0	1	1	1	0	0		Temperature Sensor Control (Write Command to External temperature sensor)	Write Command to External temperature sensor. A[7:0] = 00h [POR], B[7:0] = 00h [POR], C[7:0] = 00h [POR],														
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																	
0	1		B ₇	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀																	
0	1		C ₇	C ₆	C ₅	C ₄	C ₃	C ₂	C ₁	C ₀																	
													<table border="1"> <tr> <th>A[7:6]</th> <th>Select no of byte to be sent</th> </tr> <tr> <td>00</td> <td>Address + pointer</td> </tr> <tr> <td>01</td> <td>Address + pointer + 1st parameter</td> </tr> <tr> <td>10</td> <td>Address + pointer + 1st parameter + 2nd pointer</td> </tr> <tr> <td>11</td> <td>Address</td> </tr> </table> <p>A[5:0] – Pointer Setting B[7:0] – 1st parameter C[7:0] – 2nd parameter The command required CLKEN=1. Refer to Register 0x22 for detail.</p> <p>After this command initiated, Write Command to external temperature sensor starts. BUSY pad will output high during operation.</p>	A[7:6]	Select no of byte to be sent	00	Address + pointer	01	Address + pointer + 1st parameter	10	Address + pointer + 1st parameter + 2nd pointer	11	Address				
A[7:6]	Select no of byte to be sent																										
00	Address + pointer																										
01	Address + pointer + 1st parameter																										
10	Address + pointer + 1st parameter + 2nd pointer																										
11	Address																										
0	0	1F	0	0	0	1	1	1	1	1		IC revision Read	Read IC revision [POR 0x0D]														
1	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																	

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 17 of 35

0	0	20	0	0	1	0	0	0	0	0	0	Master Activation	<p>Activate Display Update Sequence</p> <p>The Display Update Sequence Option is located at R22h.</p> <p>BUSY pad will output high during operation. User should not interrupt this operation to avoid corruption of panel images.</p>																																																																																																
0	0	21	0	0	1	0	0	0	0	0	1	Display Update Control 1	<p>RAM content option for Display Update</p> <p>A[7:0] = 00h [POR]</p> <p>B[7:0] = 00h [POR]</p> <p>A[7:4] Red RAM option</p> <table border="1"> <tr><td>0000</td><td>Normal</td></tr> <tr><td>0100</td><td>Bypass RAM content as 0</td></tr> <tr><td>1000</td><td>Inverse RAM content</td></tr> </table> <p>A[3:0] BW RAM option</p> <table border="1"> <tr><td>0000</td><td>Normal</td></tr> <tr><td>0100</td><td>Bypass RAM content as 0</td></tr> <tr><td>1000</td><td>Inverse RAM content</td></tr> </table> <p>B[7] Source Output Mode</p> <table border="1"> <tr><td>0</td><td>Available Source from S0 to S175</td></tr> <tr><td>1</td><td>Available Source from S8 to S167</td></tr> </table>	0000	Normal	0100	Bypass RAM content as 0	1000	Inverse RAM content	0000	Normal	0100	Bypass RAM content as 0	1000	Inverse RAM content	0	Available Source from S0 to S175	1	Available Source from S8 to S167																																																																																
0000	Normal																																																																																																												
0100	Bypass RAM content as 0																																																																																																												
1000	Inverse RAM content																																																																																																												
0000	Normal																																																																																																												
0100	Bypass RAM content as 0																																																																																																												
1000	Inverse RAM content																																																																																																												
0	Available Source from S0 to S175																																																																																																												
1	Available Source from S8 to S167																																																																																																												
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																																																																																																			
0	1		B ₇	0	0	0	0	0	0	0	0																																																																																																		
0	0	22	0	0	1	0	0	0	0	1	0	Display Update Control 2	<p>Display Update Sequence Option:</p> <p>Enable the stage for Master Activation</p> <p>A[7:0]= FFh (POR)</p> <table border="1"> <thead> <tr> <th>Operating sequence</th> <th>Parameter (In Hex)</th> </tr> </thead> <tbody> <tr><td>Enable clock signal</td><td>80</td></tr> <tr><td>Disable clock signal</td><td>01</td></tr> <tr><td> </td><td> </td></tr> <tr><td>Enable clock signal</td><td>C0</td></tr> <tr><td>→ Enable Analog</td><td> </td></tr> <tr><td>Disable Analog</td><td>03</td></tr> <tr><td>→ Disable clock signal</td><td> </td></tr> <tr><td> </td><td> </td></tr> <tr><td>Enable clock signal</td><td>91</td></tr> <tr><td>→ Load LUT with DISPLAY Mode 1</td><td> </td></tr> <tr><td>→ Disable clock signal</td><td> </td></tr> <tr><td>Enable clock signal</td><td>99</td></tr> <tr><td>→ Load LUT with DISPLAY Mode 2</td><td> </td></tr> <tr><td>→ Disable clock signal</td><td> </td></tr> <tr><td> </td><td> </td></tr> <tr><td>Enable clock signal</td><td>B1</td></tr> <tr><td>→ Load temperature value</td><td> </td></tr> <tr><td>→ Load LUT with DISPLAY Mode 1</td><td> </td></tr> <tr><td>→ Disable clock signal</td><td> </td></tr> <tr><td>Enable clock signal</td><td>B9</td></tr> <tr><td>→ Load temperature value</td><td> </td></tr> <tr><td>→ Load LUT with DISPLAY Mode 2</td><td> </td></tr> <tr><td>→ Disable clock signal</td><td> </td></tr> <tr><td> </td><td> </td></tr> <tr><td>Enable clock signal</td><td>C7</td></tr> <tr><td>→ Enable Analog</td><td> </td></tr> <tr><td>→ Display with DISPLAY Mode 1</td><td> </td></tr> <tr><td>→ Disable Analog</td><td> </td></tr> <tr><td>→ Disable OSC</td><td> </td></tr> <tr><td>Enable clock signal</td><td>CF</td></tr> <tr><td>→ Enable Analog</td><td> </td></tr> <tr><td>→ Display with DISPLAY Mode 2</td><td> </td></tr> <tr><td>→ Disable Analog</td><td> </td></tr> <tr><td>→ Disable OSC</td><td> </td></tr> <tr><td> </td><td> </td></tr> <tr><td>Enable clock signal</td><td>F7</td></tr> <tr><td>→ Enable Analog</td><td> </td></tr> <tr><td>→ Load temperature value</td><td> </td></tr> <tr><td>→ DISPLAY with DISPLAY Mode 1</td><td> </td></tr> <tr><td>→ Disable Analog</td><td> </td></tr> <tr><td>→ Disable OSC</td><td> </td></tr> <tr><td>Enable clock signal</td><td>FF</td></tr> <tr><td>→ Enable Analog</td><td> </td></tr> <tr><td>→ Load temperature value</td><td> </td></tr> <tr><td>→ DISPLAY with DISPLAY Mode 2</td><td> </td></tr> <tr><td>→ Disable Analog</td><td> </td></tr> <tr><td>→ Disable OSC</td><td> </td></tr> </tbody> </table>	Operating sequence	Parameter (In Hex)	Enable clock signal	80	Disable clock signal	01			Enable clock signal	C0	→ Enable Analog		Disable Analog	03	→ Disable clock signal				Enable clock signal	91	→ Load LUT with DISPLAY Mode 1		→ Disable clock signal		Enable clock signal	99	→ Load LUT with DISPLAY Mode 2		→ Disable clock signal				Enable clock signal	B1	→ Load temperature value		→ Load LUT with DISPLAY Mode 1		→ Disable clock signal		Enable clock signal	B9	→ Load temperature value		→ Load LUT with DISPLAY Mode 2		→ Disable clock signal				Enable clock signal	C7	→ Enable Analog		→ Display with DISPLAY Mode 1		→ Disable Analog		→ Disable OSC		Enable clock signal	CF	→ Enable Analog		→ Display with DISPLAY Mode 2		→ Disable Analog		→ Disable OSC				Enable clock signal	F7	→ Enable Analog		→ Load temperature value		→ DISPLAY with DISPLAY Mode 1		→ Disable Analog		→ Disable OSC		Enable clock signal	FF	→ Enable Analog		→ Load temperature value		→ DISPLAY with DISPLAY Mode 2		→ Disable Analog		→ Disable OSC	
Operating sequence	Parameter (In Hex)																																																																																																												
Enable clock signal	80																																																																																																												
Disable clock signal	01																																																																																																												
Enable clock signal	C0																																																																																																												
→ Enable Analog																																																																																																													
Disable Analog	03																																																																																																												
→ Disable clock signal																																																																																																													
Enable clock signal	91																																																																																																												
→ Load LUT with DISPLAY Mode 1																																																																																																													
→ Disable clock signal																																																																																																													
Enable clock signal	99																																																																																																												
→ Load LUT with DISPLAY Mode 2																																																																																																													
→ Disable clock signal																																																																																																													
Enable clock signal	B1																																																																																																												
→ Load temperature value																																																																																																													
→ Load LUT with DISPLAY Mode 1																																																																																																													
→ Disable clock signal																																																																																																													
Enable clock signal	B9																																																																																																												
→ Load temperature value																																																																																																													
→ Load LUT with DISPLAY Mode 2																																																																																																													
→ Disable clock signal																																																																																																													
Enable clock signal	C7																																																																																																												
→ Enable Analog																																																																																																													
→ Display with DISPLAY Mode 1																																																																																																													
→ Disable Analog																																																																																																													
→ Disable OSC																																																																																																													
Enable clock signal	CF																																																																																																												
→ Enable Analog																																																																																																													
→ Display with DISPLAY Mode 2																																																																																																													
→ Disable Analog																																																																																																													
→ Disable OSC																																																																																																													
Enable clock signal	F7																																																																																																												
→ Enable Analog																																																																																																													
→ Load temperature value																																																																																																													
→ DISPLAY with DISPLAY Mode 1																																																																																																													
→ Disable Analog																																																																																																													
→ Disable OSC																																																																																																													
Enable clock signal	FF																																																																																																												
→ Enable Analog																																																																																																													
→ Load temperature value																																																																																																													
→ DISPLAY with DISPLAY Mode 2																																																																																																													
→ Disable Analog																																																																																																													
→ Disable OSC																																																																																																													
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																																																																																																			

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 18 of 35

0	0	24	0	0	1	0	0	1	0	0	Write RAM (Black White) / RAM 0x24	After this command, data entries will be written into the BW RAM until another command is written. Address pointers will advance accordingly For Write pixel: Content of Write RAM(BW) = 1 For Black pixel: Content of Write RAM(BW) = 0
0	0	26	0	0	1	0	0	1	1	0	Write RAM (RED) / RAM 0x26	After this command, data entries will be written into the RED RAM until another command is written. Address pointers will advance accordingly. For Red pixel: Content of Write RAM(RED) = 1 For non-Red pixel [Black or White]: Content of Write RAM(RED) = 0
0	0	27	0	0	1	0	0	1	1	1	Read RAM	After this command, data read on the MCU bus will fetch data from RAM. According to parameter of Register 41h to select reading RAM0x24/ RAM0x26, until another command is written. Address pointers will advance accordingly. The 1 st byte of data read is dummy data.
0	0	28	0	0	1	0	1	0	0	0	VCOM Sense	Enter VCOM sensing conditions and hold for duration defined in 29h before reading VCOM value. The sensed VCOM voltage is stored in register The command required CLKEN=1 and ANALOGEN=1 Refer to Register 0x22 for detail. BUSY pad will output high during operation.
0	0	29	0	0	1	0	1	0	0	1	VCOM Sense Duration	Stabling time between entering VCOM sensing mode and reading acquired. A[3:0] = 9h, duration = 10s. VCOM sense duration = (A[3:0]+1) sec
0	1		0	1	0	0	A ₃	A ₂	A ₁	A ₀		
0	0	2A	0	0	1	0	1	0	1	0	Program VCOM OTP	Program VCOM register into OTP The command required CLKEN=1. Refer to Register 0x22 for detail. BUSY pad will output high during operation.

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 19 of 35

Command Table											Command	Description				
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0						
0	0	2C	0	0	1	0	1	1	0	0	Write VCOM register	Write VCOM register from MCU interface A[7:0] = 00h [POR]				
0	1		A7	A6	A5	A4	A3	A2	A1	A0						
													A[7:0]	VCOM	A[7:0]	VCOM
													08h	-0.2	44h	-1.7
													0Ch	-0.3	48h	-1.8
													10h	-0.4	4Ch	-1.9
													14h	-0.5	50h	-2
													18h	-0.6	54h	-2.1
													1Ch	-0.7	58h	-2.2
													20h	-0.8	5Ch	-2.3
													24h	-0.9	60h	-2.4
													28h	-1	64h	-2.5
													2Ch	-1.1	68h	-2.6
													30h	-1.2	6Ch	-2.7
											34h	-1.3	70h	-2.8		
											38h	-1.4	74h	-2.9		
											3Ch	-1.5	78h	-3		
											40h	-1.6	Other	NA		
0	0	2D	0	0	1	0	1	1	0	1	OTP Register Read for Display Option	Read Register for Display Option: A[7:0]: VCOM OTP Selection (Command 0x37, Byte A) B[7:0]: VCOM Register (Command 0x2C) C[7:0]~G[7:0]: Display Mode (Command 0x37, Byte B to Byte F) [5 bytes] H[7:0]~K[7:0]: Waveform Version (Command 0x37, Byte G to Byte J) [4 bytes]				
1	1		A7	A6	A5	A4	A3	A2	A1	A0						
1	1		B7	B6	B5	B4	B3	B2	B1	B0						
1	1		C7	C6	C5	C4	C3	C2	C1	C0						
1	1		D7	D6	D5	D4	D3	D2	D1	D0						
1	1		E7	E6	E5	E4	E3	E2	E1	E0						
1	1		F7	F6	F5	F4	F3	F2	F1	F0						
1	1		G7	G6	G5	G4	G3	G2	G1	G0						
1	1		H7	H6	H5	H4	H3	H2	H1	H0						
1	1		I7	I6	I5	I4	I3	I2	I1	I0						
1	1		J7	J6	J5	J4	J3	J2	J1	J0						
1	1		K7	K6	K5	K4	K3	K2	K1	K0						
0	0	2E	0	0	1	0	1	1	1	0	User ID Read	Read 10 Byte User ID stored in OTP: A[7:0]~J[7:0]: UserID (R38, Byte A and Byte J) [10 bytes]				
1	1		A7	A6	A5	A4	A3	A2	A1	A0						
1	1		B7	B6	B5	B4	B3	B2	B1	B0						
1	1		C7	C6	C5	C4	C3	C2	C1	C0						
1	1		D7	D6	D5	D4	D3	D2	D1	D0						
1	1		E7	E6	E5	E4	E3	E2	E1	E0						
1	1		F7	F6	F5	F4	F3	F2	F1	F0						
1	1		G7	G6	G5	G4	G3	G2	G1	G0						
1	1		H7	H6	H5	H4	H3	H2	H1	H0						
1	1		I7	I6	I5	I4	I3	I2	I1	I0						
1	1		J7	J6	J5	J4	J3	J2	J1	J0						
0	0	2F	0	0	1	0	1	1	1	1			Status Bit Read	Read IC status Bit [POR 0x01] A[5]: HV Ready Detection flag [POR=0] 0: Ready 1: Not Ready A[4]: VCI Detection flag [POR=0] 0: Normal 1: VCI lower than the Detect level A[3]: [POR=0] A[2]: Busy flag [POR=0] 0: Normal 1: BUSY A[1:0]: Chip ID [POR=01] Remark: A[5] and A[4] status are not valid after RESET, they need to be initiated by command 0x14 and command 0x15 respectively.		
1	1		0	0	A5	A4	0	0	A1	A0						

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 20 of 35

Command Table												
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description
0	0	30	0	0	1	1	0	0	0	0	Program WS OTP	<p>Program OTP of Waveform Setting The contents should be written into RAM before sending this command.</p> <p>The command required CLKEN=1. Refer to Register 0x22 for detail. BUSY pad will output high during operation.</p>
0	0	31	0	0	1	1	0	0	0	1	Load WS OTP	<p>Load OTP of Waveform Setting</p> <p>The command required CLKEN=1. Refer to Register 0x22 for detail.</p> <p>BUSY pad will output high during operation.</p>
0	0	32	0	0	1	1	0	0	1	0	Write LUT register	<p>Write LUT register from MCU interface [227 bytes], which contains the content of VS[nX-LUTm], TP[nX], RP[n], SR[nXY], FR and XON[nXY] Refer to Session 6.7 WAVEFORM SETTING</p>
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	1		B ₇	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		
0	1		:	:	:	:	:	:	:	:		
0	1			
0	0	34	0	0	1	1	0	1	0	0	CRC calculation	<p>CRC calculation command For details, please refer to SSD1680A application note.</p> <p>BUSY pad will output high during operation.</p>
0	0	35	0	0	1	1	0	1	0	1	CRC Status Read	<p>CRC Status Read A[15:0] is the CRC read out value</p>
1	1		A ₁₅	A ₁₄	A ₁₃	A ₁₂	A ₁₁	A ₁₀	A ₉	A ₈		
1	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	0	36	0	0	1	1	0	1	1	0	Program OTP selection	<p>Program OTP Selection according to the OTP Selection Control [R37h and R38h]</p> <p>The command required CLKEN=1. Refer to Register 0x22 for detail. BUSY pad will output high during operation.</p>

DATE	AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM		YES	YMS296152-0266CAAMFGN	Page 21 of 35

Command Table												Command	Description
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0			
0	0	37	0	0	1	1	0	1	1	1	Write Register for Display Option	Write Register for Display Option A[7] Spare VCOM OTP selection 0: Default [POR] 1: Spare B[7:0] Display Mode for WS[7:0] C[7:0] Display Mode for WS[15:8] D[7:0] Display Mode for WS[23:16] 0: Display Mode 1 1: Display Mode 2 F[6]: Ping-Pong for Display Mode 2 0: RAM Ping-Pong disable [POR] 1: RAM Ping-Pong enable G[7:0]~J[7:0] module ID /waveform version. Remarks: 1) A[7:0]~J[7:0] can be stored in OTP 2) RAM Ping-Pong function is not support for Display Mode 1	
0	1		A7	0	0	0	0	0	0	0			
0	1		B7	B6	B5	B4	B3	B2	B1	B0			
0	1		C7	C6	C5	C4	C3	C2	C1	C0			
0	1		D7	D6	D5	D4	D3	D2	D1	D0			
0	1		E7	E6	E5	E4	E3	E2	E1	E0			
0	1		0	F6	0	0	F3	F2	F1	F0			
0	1		G7	G6	G5	G4	G3	G2	G1	G0			
0	1		H7	H6	H5	H4	H3	H2	H1	H0			
0	1		I7	I6	I5	I4	I3	I2	I1	I0			
0	1		J7	J6	J5	J4	J3	J2	J1	J0			
0	0	38	0	0	1	1	1	0	0	0	Write Register for User ID	Write Register for User ID A[7:0]~J[7:0]: UserID [10 bytes] Remarks: A[7:0]~J[7:0] can be stored in OTP	
0	1		A7	A6	A5	A4	A3	A2	A1	A0			
0	1		B7	B6	B5	B4	B3	B2	B1	B0			
0	1		C7	C6	C5	C4	C3	C2	C1	C0			
0	1		D7	D6	D5	D4	D3	D2	D1	D0			
0	1		E7	E6	E5	E4	E3	E2	E1	E0			
0	1		F7	F6	F5	F4	F3	F2	F1	F0			
0	1		G7	G6	G5	G4	G3	G2	G1	G0			
0	1		H7	H6	H5	H4	H3	H2	H1	H0			
0	1		I7	I6	I5	I4	I3	I2	I1	I0			
0	1		J7	J6	J5	J4	J3	J2	J1	J0			
0	0	39	0	0	1	1	1	0	0	1	OTP program mode	OTP program mode A[1:0] = 00: Normal Mode [POR] A[1:0] = 11: Internal generated OTP programming voltage : User is required to EXACTLY follow the reference code sequences	
0	1		0	0	0	0	0	0	A1	A0			

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 22 of 35

Command Table											Command	Description		
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0				
0	0	3C	0	0	1	1	1	1	0	0	Border Waveform Control	Select border waveform for VBD A[7:0] = C0h [POR], set VBD as HIZ. A [7:6] :Select VBD option		
0	1		A7	A6	A5	A4	0	0	A1	A0			A[7:6]	Select VBD as
													00	GS Transition, Defined in A[2] and A[1:0]
													01	Fix Level, Defined in A[5:4]
													10	VCOM
													11[POR]	HiZ
													A [5:4] Fix Level Setting for VBD	
													A[5:4]	VBD level
													00	VSS
													01	VSH1
													10	VSL
													11	VSH2
													A [1:0] GS Transition setting for VBD VBD Level Selection: 00b: VCOM ; 01b: VSH1; 10b: VSL; 11b: VSH2	
											A[1:0]	VBD Transition		
											00	LUT0		
											01	LUT1		
											10	LUT2		
											11	LUT3		
0	0	3F	0	0	1	1	1	1	1	1	End Option (EOPT)	Option for LUT end Data bytes should be set for this command or programmed into Waveform setting.		
0	1		A7	A6	A5	A4	A3	A2	A1	A0			22h	Normal.
													07h	Source output level keep previous output before power off
0	0	41	0	1	0	0	0	0	0	1	Read RAM Option	Read RAM Option A[0]= 0 [POR] 0 : Read RAM corresponding to RAM0x24 1 : Read RAM corresponding to RAM0x26		
0	1		0	0	0	0	0	0	0	A0				
0	0	44	0	1	0	0	0	1	0	0	Set RAM X - address Start / End position	Specify the start/end positions of the window address in the X direction by an address unit for RAM A[5:0]: XSA[5:0], XStart, POR = 00h B[5:0]: XEA[5:0], XEnd, POR = 15h		
0	1		0	0	A5	A4	A3	A2	A1	A0				
0	1		0	0	B5	B4	B3	B2	B1	B0				
0	0	45	0	1	0	0	0	1	0	1	Set Ram Y- address Start / End position	Specify the start/end positions of the window address in the Y direction by an address unit for RAM A[8:0]: YSA[8:0], YStart, POR = 000h B[8:0]: YEA[8:0], YEnd, POR = 127h		
0	1		A7	A6	A5	A4	A3	A2	A1	A0				
0	1		0	0	0	0	0	0	0	A8				
0	1		B7	B6	B5	B4	B3	B2	B1	B0				
0	1		0	0	0	0	0	0	0	B8				

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 23 of 35

Command Table											Command	Description																																								
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0																																										
0	0	46	0	1	0	0	0	1		0	Auto Write RED RAM for Regular Pattern	Auto Write RED RAM for Regular Pattern A[7:0] = 00h [POR]																																								
0	1		A ₇	A ₆	A ₅	A ₄	0	A ₂	A ₁	A ₀		<p>A[7]: The 1st step value, POR = 0 A[6:4]: Step Height, POR= 000 Step of alter RAM in Y-direction according to Gate</p> <table border="1"> <thead> <tr> <th>A[6:4]</th> <th>Height</th> <th>A[6:4]</th> <th>Height</th> </tr> </thead> <tbody> <tr> <td>000</td> <td>8</td> <td>100</td> <td>128</td> </tr> <tr> <td>001</td> <td>16</td> <td>101</td> <td>256</td> </tr> <tr> <td>010</td> <td>32</td> <td>110</td> <td>296</td> </tr> <tr> <td>011</td> <td>64</td> <td>111</td> <td>NA</td> </tr> </tbody> </table> <p>A[2:0]: Step Width, POR= 000 Step of alter RAM in X-direction according to Source</p> <table border="1"> <thead> <tr> <th>A[2:0]</th> <th>Width</th> <th>A[2:0]</th> <th>Width</th> </tr> </thead> <tbody> <tr> <td>000</td> <td>8</td> <td>100</td> <td>128</td> </tr> <tr> <td>001</td> <td>16</td> <td>101</td> <td>176</td> </tr> <tr> <td>010</td> <td>32</td> <td>110</td> <td>NA</td> </tr> <tr> <td>011</td> <td>64</td> <td>111</td> <td>NA</td> </tr> </tbody> </table> <p>BUSY pad will output high during operation.</p>	A[6:4]	Height	A[6:4]	Height	000	8	100	128	001	16	101	256	010	32	110	296	011	64	111	NA	A[2:0]	Width	A[2:0]	Width	000	8	100	128	001	16	101	176	010	32	110	NA	011	64	111	NA
A[6:4]	Height	A[6:4]	Height																																																	
000	8	100	128																																																	
001	16	101	256																																																	
010	32	110	296																																																	
011	64	111	NA																																																	
A[2:0]	Width	A[2:0]	Width																																																	
000	8	100	128																																																	
001	16	101	176																																																	
010	32	110	NA																																																	
011	64	111	NA																																																	
0	0	47	0	1	0	0	0	1	1	1	Auto Write B/W RAM for Regular Pattern	Auto Write B/W RAM for Regular Pattern A[7:0] = 00h [POR]																																								
0	1		A ₇	A ₆	A ₅	A ₄	0	A ₂	A ₁	A ₀		<p>A[7]: The 1st step value, POR = 0 A[6:4]: Step Height, POR= 000 Step of alter RAM in Y-direction according to Gate</p> <table border="1"> <thead> <tr> <th>A[6:4]</th> <th>Height</th> <th>A[6:4]</th> <th>Height</th> </tr> </thead> <tbody> <tr> <td>000</td> <td>8</td> <td>100</td> <td>128</td> </tr> <tr> <td>001</td> <td>16</td> <td>101</td> <td>256</td> </tr> <tr> <td>010</td> <td>32</td> <td>110</td> <td>296</td> </tr> <tr> <td>011</td> <td>64</td> <td>111</td> <td>NA</td> </tr> </tbody> </table> <p>A[2:0]: Step Width, POR= 000 Step of alter RAM in X-direction according to Source</p> <table border="1"> <thead> <tr> <th>A[2:0]</th> <th>Width</th> <th>A[2:0]</th> <th>Width</th> </tr> </thead> <tbody> <tr> <td>000</td> <td>8</td> <td>100</td> <td>128</td> </tr> <tr> <td>001</td> <td>16</td> <td>101</td> <td>176</td> </tr> <tr> <td>010</td> <td>32</td> <td>110</td> <td>NA</td> </tr> <tr> <td>011</td> <td>64</td> <td>111</td> <td>NA</td> </tr> </tbody> </table> <p>During operation, BUSY pad will output high.</p>	A[6:4]	Height	A[6:4]	Height	000	8	100	128	001	16	101	256	010	32	110	296	011	64	111	NA	A[2:0]	Width	A[2:0]	Width	000	8	100	128	001	16	101	176	010	32	110	NA	011	64	111	NA
A[6:4]	Height	A[6:4]	Height																																																	
000	8	100	128																																																	
001	16	101	256																																																	
010	32	110	296																																																	
011	64	111	NA																																																	
A[2:0]	Width	A[2:0]	Width																																																	
000	8	100	128																																																	
001	16	101	176																																																	
010	32	110	NA																																																	
011	64	111	NA																																																	
0	0	4E	0	1	0	0	1	1	1	0	Set RAM X address counter	Make initial settings for the RAM X address in the address counter (AC) A[5:0]: 00h [POR].																																								
0	1		0	0	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																																										
0	0	4F	0	1	0	0	1	1	1	1	Set RAM Y address counter	Make initial settings for the RAM Y address in the address counter (AC) A[8:0]: 000h [POR].																																								
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																																										
0	1		0	0	0	0	0	0	0	A ₈																																										
0	0	7F	0	1	1	1	1	1	1	1	NOP	This command is an empty command; it does not have any effect on the display module. However it can be used to terminate Frame Memory Write or Read Commands.																																								

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 24 of 35

8. Optical Specifications

Measurements are made with that the illumination is under an angle of 45 degree, the detection is perpendicular unless otherwise specified

Symbol	Parameter	Conditions	Min	Typ.	Max	Units	Notes
R	White Reflectivity	White	30	35	-	%	8-1
CR	Contrast Ratio	Indoor	8:1		-		8-2
GN	2Grey Level	-		$DS+(WS-DS)*n(m-1)$			8-3
T update	Image update time	at 25 °C		3	-	sec	
Life		Topr		1000000times or 5years			

Notes: 8-1. Luminance meter: Eye-One Pro Spectrophotometer.

8-2. CR=Surface Reflectance with all white pixel/Surface Reflectance with all black pixels.

8-3 WS: White state, DS: Dark state

9. Handling, Safety and Environment Requirements

Warning

The display glass may break when it is dropped or bumped on a hard surface. Handle with care. Should the display break, do not touch the electrophoretic material. In case of contact with electrophoretic material, wash with water and soap.

Caution

The display module should not be exposed to harmful gases, such as acid and alkali gases, which corrode electronic components. Disassembling the display module.

Disassembling the display module can cause permanent damage and invalidates the warranty agreements.

Observe general precautions that are common to handling delicate electronic components. The glass can break and front surfaces can easily be damaged. Moreover the display is sensitive to static electricity and other rough environmental conditions.

Data sheet status	
Product specification	This data sheet contains final product specifications.
Limiting values	
Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.	
Application information	
Where application information is given, it is advisory and does not form part of the specification.	

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 25 of 35


10. Reliability test

NO	Test items	Test condition
1	Low-Temperature Storage	T = -25°C, 240 h Test in white pattern
2	High-Temperature Storage	T = +70°C, RH=40% ,240h Test in white pattern
3	High-Temperature Operation	T = +50°C, RH = 30% ,240h
4	Low-Temperature Operation	0°C, 240h
5	High-Temperature, High-Humidity Operation	T=+40°C, RH=90%,240h
6	High Temperature, High Humidity Storage	T=+60°C, RH=80%,240h Test in white pattern
7	Temperature Cycle	1 cycle:[-25°C 30min]→[+70 °C 30 min] : 100 cycles Test in white pattern
8	UV exposure Resistance	765W/m ² for 168hrs,40 °C Test in white pattern
9	ESD Gun	Air+/-15KV;Contact+/-8KV (Test finished product shell,not display only) Air+/-8KV;Contact+/-6KV (Naked EPD display,no including IC and FPC area) Air+/-4KV;Contact+/-2KV (Naked EPD display,including IC and FPC area)

Note: Put in normal temperature for 1hour after test finished, display performance is ok.


DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 26 of 35

11. Block Diagram



DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 27 of 35

12. Typical Application Circuit with SPI Interface




Part Name	Value	Requirements/Reference Part
C0-C1	1uF	X5R/X7R; Voltage Rating : 6V or 25V
C2-C7	1uF	0402/0603/0805; X5R/X7R; Voltage Rating : 25V
C8	0.47uF, 1uF	0402/0603/0805; X7R; Voltage Rating : 25V
R1	2.2 ohm	0402/0603/0805; 1% variation, ≥ 0.05W
D1-D3	Diode	MBR0530 1) Reverse DC voltage ≥ 30V 2) I _o ≥ 500mA 3) Forward voltage ≤ 430mV
Q1	NMOS	Si1304BDL/NX3008NBK 1) Drain-Source breakdown voltage ≥ 30V 2) V _{gs(th)} = 0.9V (Typ), 1.3V (Max) 3) R _{ds on} ≤ 2.1Ω @ V _{gs} = 2.5V
L1	47uH	CDRH2D18 / LDNP-470NC I _o = 500mA (Max)
U1	0.5mm ZIF socket	24pins, 0.5mm pitch

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 28 of 35


13. Typical Operating Sequence

13.1 Normal Operation Flow



DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 29 of 35

13.2 OTP Operation Flow



13.3 OTP Operation Reference Program Code

Procedure and Code sequence for WS & TR in the OTP			
Step	Action	Value/Data	Comment
1	Command 0x12		SWRESET
2	wait for BUSY LOW	bound by a timeout value	
3	Command 0x21	0x00 0x00	Display Update Control 1
4	Command 0x11	0x07	Data entry mode setting
5	Command 0x44	0x00 0x13	Set RAM X address
6	Command 0x45	0x00 0x00 0x27 0x01	Set RAM Y address
7	Command 0x4E	0x00	Set RAM X address counter = 0
8	Command 0x4F	0x00 0x00	Set RAM Y address counter = 0
9	Command 0x47	0x65	Clear RAM content as zero
10	wait for BUSY LOW	bound by a timeout value	
11	Command 0x22	0x80	Master Configuration: Enable Clock
12	Command 0x20		Master Activation
13	wait for BUSY LOW	bound by a timeout value	
14	Command 0x4E	0x00	Set RAM X address counter = 0
15	Command 0x4F	0x00 0x00	Set RAM Y address counter = 0
16	Command 0x24	RAM:5640 byte	Write Waveform setting and Temperature Range into RAM
17	Command 0x4E	0x00	Set RAM X address counter = 0
18	Command 0x4F	0x00 0x00	Set RAM Y address counter = 0
19	Command 0x34		CRC Calculation from (0x00,0x000) to (0x13,0x127), total 5920 byte
20	wait for BUSY LOW	bound by a timeout value	
21	Command 0x35	Parameter 1 Parameter 2	CRC Status Read Parameter 1 is Most-Significant Byte, Parameter 2 is Least-Significant Byte.
22		MCU records these two bytes CRC code for after-OTP checking	
23	Command 0x39	0x03	Set internal OTP programming voltage
24	Command 0x03	0x07	
25	Command 0x04	0xC1 0xA8 0x1A	
26	Command 0x22	0xC0	Master Configuration: Enable Analog and Clock
27	Command 0x20		Master Activation
28	wait for BUSY LOW	bound by a timeout value	
29	Command 0x4E	0x00 0x00	Set RAM X address counter = 0
30	Command 0x4F	0x00 0x00	Set RAM Y address counter = 0
31	Command 0x30		Program Waveform Setting and Temperature Range into OTP.
32	Command 0x22	0x03	Master Configuration: Disable Analog and Clock
33	Command 0x20		Master Activation
34	wait for BUSY LOW	bound by a timeout value	
35	Command 0x12		SWRESET
36	wait for BUSY LOW	bound by a timeout value	

DATE	AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM		YES	YMS296152-0266CAAMFGN	Page 30 of 35

14. Part Number Definition

TBD

15. Inspection condition

15.1 Environment


Temperature: $25 \pm 3^{\circ}\text{C}$

Humidity: $55 \pm 10\% \text{RH}$


15.2 Illuminance

Brightness: 1200~1500LUX; distance: 20-30CM; Angle: Relate 30 surround.

15.3 Inspect method





15.4 Display area



DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 31 of 35

15.5 Inspection standard

15.5.1 Electric inspection standard

NO.	Item	Standard	Defect level	Method	Scope
1	Display	Display complete Display uniform	MA		
2	Black/White spots	 $D \leq 0.25\text{mm}$, Allowed $0.25\text{mm} < D \leq 0.4\text{mm}$, $N \leq 3$, and Distance $\geq 5\text{mm}$ $0.4\text{mm} < D$ Not Allow	MI	Visual inspection	
3	Black/White spots (No switch)	 $L \leq 0.6\text{mm}$, $W \leq 0.2\text{mm}$, $N \leq 1$ $L \leq 2.0\text{mm}$, $W > 0.2\text{mm}$, Not Allow $L > 0.6\text{mm}$, Not Allow		Visual/ Inspection card	Zone A
4	Ghost image	Allowed in switching process	MI	Visual inspection	
5	Flash spots/ Larger FPL size	Flash spots in switching, Allowed FPL size larger than viewing area, Allowed	MI	Visual/ Inspection card	Zone A Zone B
6	Display wrong/Missing	All appointed displays are showed correct	MA	Visual inspection	Zone A
7	Short circuit/ Circuit break/ Display abnormal	Not Allow			

DATE AUG.12.2020

Version

1.1

TECHNICAL SPECIFICATION






LCM

YES

YMS296152-0266CAAMFGN

Page 32 of 35

15.5.2 Appearance inspection standard

NO.	Item	Standard	Defect level	Method	Scope
1	B/W spots /Bubble/ Foreign bodies/ Dents	 <p>$D = (L + W) / 2$</p> <p>$D \leq 0.25\text{mm}$, Allowed $0.25\text{mm} < D \leq 0.4\text{mm}$, $N \leq 3$ $D > 0.4\text{mm}$, Not Allow</p>	MI	Visual inspection	Zone A
2	Glass crack	Not Allow	MA	Visual / Microscope	Zone A Zone B
3	Dirty	Allowed if can be removed	MI		Zone A Zone B
4	Chips/Scratch/ Edge crown	 <p>$X \leq 3\text{mm}, Y \leq 0.5\text{mm}$ And without affecting the electrode is permissible</p>  <p>$2\text{mm} \leq X$ or $2\text{mm} \leq Y$ Not Allow</p>  <p>$W \leq 0.1\text{mm}, L \leq 5\text{mm}$, No harm to the electrodes and $N \leq 2$ allow</p>	MI	Visual / Microscope	Zone A Zone B
5	TFT Cracks	Not Allow	MA	Visual / Microscope	Zone A Zone B
6	Dirty/ foreign body	Allowed if can be removed/ allow	MI	Visual / Microscope	Zone A / Zone B
7	FPC broken/ Goldfingers oxidation/ scratch	 <p>Not Allow</p>	MA	Visual / Microscope	Zone B

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 33 of 35

8	TFT edge bulge /TFT chromatic aberration	TFT edge bulge: X≤3mm, Y≤0.3mm Allowed TFT chromatic aberration :Allowed	MI	Visual / Microscope	Zone A Zone B
9	PCB damaged/ Poor welding/ Curl	PCB (Circuit area) damaged Not Allow PCB Poor welding Not Allow PCB Curl≤1%	MI	Visual / Ruler	Zone B
10	Edge glue height/ Edge glue bubble	Edge Adhesives H≤PS surface (Including protect film) Edge adhesives seep in≤1/2 Margin width Length excluding Edge adhesives bubble: bubble Width ≤1/2 Margin width; Length ≤0.5mm。 n≤5			
11	Protect film	Surface scratch but not effect protect function, Allowed			
12	Silicon glue	Thickness ≤PS surface(With protect film): Full cover the IC; Shape: The width on the FPC ≤ 0.5mm (Front) The width on the FPC≤1.0mm (Back) smooth surface,No obvious raised.	MI	Visual Inspection	
13	Warp degree (TFT substrate)	t≤2.0mm	MI	Ruler	
14	Color difference in COM area (Silver point area)	Allowed		Visual Inspection	

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 34 of 35


16. Packaging

<i>CUSTOMER'S APPROVED:</i>	<i>DATE: 2020.06.19</i>	<i>PAGE: 1/1</i>
-----------------------------	-------------------------	------------------


PRODUCT PART NO.:YMS296152-0266CAAMFGN
PACKING TYPE: BY PET TRAY(TPET296152-0266A)

PACKLING ORDER:


1) Putting 21 pcs Modules on each PET tray.And cover a dedicated EPE film.




2) Putting 9 pcs PET trays together with 1 empty tray on the top of PET tray. Insert in the ESD bag, add desiccant in the ESD bag.




3) the tray together with rubber band




4) Putting in the inner small carton



5) Putting 5 small cartons into one outcarton



6) Packing finished



Note:21 pcs in a tray, 9 trays in a inner carton, 5 inner cartons in a out carton, so 21x9x5=945pcs/Outcarton
Dimension (Small carton): 385*325*87mm Dimension (Out carton): 394*344*470mm

<i>NO. YMS296152-0266CAAMFGN</i>	<i>Ver.1</i>	Draw: _____	Chk: _____	Apv: _____
<i>Yes Optoelectronics Co.,Ltd</i>				

DATE AUG.12.2020	Version	1.1	TECHNICAL SPECIFICATION
LCM	YES	YMS296152-0266CAAMFGN	Page 35 of 35